FEATURES:

• 3 channels

509001

- Powers three separate 700 Series accelerometers and DC decouples the output
- Battery powered (line adaptor optional)
- Battery condition light
- Uses common 9 VDC transistor batteries
- Can drive up to 50 ft. of cable

Models P703B Three Channel Power Unit

n

SPECIFICATIONS

0

INPUT CHARACTERISTICS Voltage to Transducer Current to Transducer, ±20% Maximum Input Voltage	27 VDC ¹ 2.4 mA DC 10 V rms
OUTPUT CHARACTERISTICS Output Impedance (accelerometer attached to input) Recommended Load Impedance	same as transducer >100 kΩ
TRANSFER CHARACTERISTICS Frequency Response Channels Channel Separation	same as transducer 3 >80 dB
BATTERY TEST CIRCUIT LED Lights Battery Life	>18 VDC >40 hours
POWER REQUIREMENTS Batteries	(3) 9V alkaline
ENVIRONMENTAL Temperature Range	0 to 55°C
PHYSICAL CHARACTERISTICS Size Weight Connectors: Signal Input Signal Output	3" width, 2.4" height, 4" depth 0.84 lb BNC BNC

NOTES: ¹ 25.2 VDC when using Ni-Cad batteries.
 ² For extended operation, the NC3 Ni-Cad Battery Kit should be used (see accessories section).

OPTIONS: • Model P703BT for use with Models 733 and 993 triaxial accelerometers.

ACCESSORIES SUPPLIED: (3) 9V alkaline batteries.

ACCESSORIES AVAILABLE: NC3 Ni-Cad battery kit; LA704B (110V) Line Adaptor; LA704B-220 (220V) Line Adaptor; BNC Series adaptors

(6

98446 Rev.G 10/01



n

21 Firstfield Road, Gaithersburg, MD 20878 • Tel 301-330-8811 • Fax 301-330-8873 •1-800-WILCOXON • Email sensors@wilcoxon.com • Web www.wilcoxon.com

Due to continued research and development, Wilcoxon Research reserves the right to amend this specification without notice.

Model P703B Operating Instructions

Product Features and Connections



Use LA704B Line Adaptor to power unit from line voltage without batteries installed or to charge NiCad batteries.

CAUTION: DO NOT ATTEMPT TO RECHARGE ALKALINES WITH THE LA704B. Alkaline batteries may EXPLODE or leak corrosive fluids.

Test for Proper Operation

To check the Model P703B for proper operation:

- Use a digital multimeter to verify that the proper voltage and current are available at the transducer connector.
- Substitute an Oscillator for the transducer.
- Follow the connection to the power unit as shown at right.
- The unit should have unity gain.



-FOR TECHNICAL ASSISTANCE-Please contact your Applications Engineer at Wilcoxon Research, Inc. 1-800-WILCOXON • 301-330-8811 • Fax 301-330-8873